

Texas TeleSys, Inc.

Your Telecom Solution! 512.468.8392

Changing Company Greeting Menu Prompt

Feature 983

Log: (Password) See Below

For 2 Digit Extensions 120000

For 3 Digit Extensions 1020000

For 4 Digit Extensions 10020000

System Display Admin
 MBOX AA OTHER

Press AA.

System Display Auto Atdt Admin
 GRTG TABLE LINES

Press GRTG.

Enter <Greeting Table Number 1>

Press OK.

System Display Greeting <X>
 RETRY PLAY REC

Press REC.

Press OK to end your recording.

System Display Accept Greeting?
 RETRY PLAY OK

To Listen to the Greeting, press Play. To Rerecord, press RETRY.

Press OK to accept Greeting.